

Setup Configuration Of: 3G, GPRS, EDGE, MMS For Maxis, Celcom & DiGi

Final Updates - February 2008

This could help you to configure your mobile phone (sony ericsson, nokia, siemens etc). This guide is example and you must do the option yourself. Note that IPv4 (may) doesn't exist in SE or siemens. Certain mobile doesn't support OTA. So, I sent a manual configuration. Sorry, no 3G setup for Celcom except you use Nokia, you can get it at a website below. For OTA:

Nokia (all): <https://nokiags.wdsglobal.com/standard?siteLanguageId=118>

Maxis (all): <http://www.maxis.com.my/3G/about3G.asp>

Digi (MMS, GPRS & EDGE):

http://www.digi.com.my/data_services/gprs/...fig.do?page=web

Celcom (MMS & GPRS):

<http://www.celcom.com.my/cep/productservic...RSMMS/main.html>

Maxis

OTA at <http://www.maxis.com.my/3G/about3G.asp> and choose option 3G Phone Configuration

Manual WAP Settings

- On Desk, tab Control Panel -> Internet setup. (or similar)
- Tab New access pt. and tab No, then tab Next and key in the following:

Connection name: Maxis GPRS

Data bearer: GPRS

- Tab Next

Network type: IPv4

Auto-retrieve access point: (Unchecked)

Access point: net

- Tab Next and key in the following.

Prompt password at every login: (Unchecked)

Username: maxis

Password: wap

- Tab Next then tab Finish and OK to complete the setup.
- Homepage: <http://wap.maxis.com.my/wml/index.wml>
- Session Mode: Permanent
- IP adress: 202.075.133.049
- Login Type: Automatic,
- Authentication Type: Normal

MMS Settings

OTA at <http://www.maxis.com.my/3G/about3G.asp> and choose option 3G Phone Configuration

- On Desk, tab Messaging and then press the Menu key -> Tools -> Message settings -> Multimedia message...(or similar)
- Tab Internet setup, then tab Next and key in the following:
Internet settings name: Maxis MMS
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: net
- Tab Next and key in the following.
Prompt password at every login: (Unchecked)
Username: maxis
Password: wap
- Tab Next then tab Advanced, under Proxies, key in the following:
Protocol: HTTP
Use proxy: (Checked)
Proxy server address: 202.75.133.49
Port number: 80
- Tab OK then Finish
- Under Homepage, key in <http://172.16.74.100:10021/mmsc> and tab OK to complete the setup.
- To send a MMS, under the Messaging menu, tab New multimedia msg.

DiGi

OTA at http://www.digi.com.my/data_services/gprs/...fig.do?page=web

Manual WAP Settings

- On Desk, tab Control Panel -> Internet setup. (or similar)
- Tab New access pt. and tab No, then tab Next and key in the following:
Connection name: DiGi GPRS
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: digiwap
- Tab Next and key in the following.
Prompt password at every login: (Unchecked)
Username: digi
Password: digi
- Tab Next then tab Finish and OK to complete the setup.

MMS Settings

OTA at http://www.digi.com.my/data_services/gprs/...fig.do?page=web

- On Desk, tab Messaging and then press the Menu key -> Tools -> Message settings -> Multimedia message... (or similar)

- Tab Internet setup, then tab Next and key in the following:
Internet settings name: DiGi MMS
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: digimms
- Tab Next and key in the following.
Prompt password at every login: (Unchecked)
Username: mms
Password: mms
- Tab Next then tab Advanced, under Proxies, key in the following:
Protocol: HTTP
Use proxy: (Checked)
Proxy server address: 203.92.128.160
Port number: 80
- Tab OK then Finish
- Under Homepage, key in <http://mms.digi.com.my/servlets/mms> and tab OK to complete the setup.
- To send a MMS, under the Messaging menu, tab New multimedia msg.

Added on August 16, 2008, 11:08 am Celcom

Celcom (MMS & GPRS):

<http://www.celcom.com.my/cep/productservic...RSMMS/main.html>

Go to Write Message.

- Type gprspre (for prepaid) send to 95000 or b Type gprspost (for postpaid) send to 95000
- You will receive the settings & save / install all settings.
- You will be charge SMS send RM0.15 and SMS received RM0.40

Or refer to manual at http://www.channelx.com.my/mdp/gprs/wap_config.jsp and <http://www.celcom.com.my/cep/productservic...RSMMS/main.html>

- Manual WAP GPRS Settings
- On Desk, tab Control Panel -> Internet setup.(or similar)
- Tab New access pt. and tab No, then tab Next and key in the following:
Connection name: Celcom GPRS
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: celcom.net.my (Postpaid)
Access point: celcom (Prepaid)
- Tab Next and key in the following.
Prompt password at every login: (Unchecked)
Username: (Blank)
Password: (Blank)
- Tab Next then tab Finish and OK to complete the setup.

MMS Settings

Or refer to manual at http://www.channelx.com.my/mdp/gprs/wap_config.jsp and <http://www.celcom.com.my/cep/productservic...RSMMS/main.html>

- On Desk, tab Messaging and then press the Menu key -> Tools -> Message settings -> Multimedia message...(or similar)
- Tab Internet setup, then tab Next and key in the following:
Internet settings name: Celcom MMS
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: mms.celcom.net.my (Postpaid)
Access point: celcom (Prepaid)
- Tab Next and key in the following.
Prompt password at every login: (Unchecked)
Username: (Blank)
Password: (Blank)
- Tab Next then tab Advanced, under Proxies, key in the following:
Protocol: HTTP
Use proxy: (Checked)
Proxy server address: 10.128.1.242
Port number: 8080
- Tab OK then Finish
- Under Homepage, key in <http://mms.celcom.net.my> and tab OK to complete the setup.
- To send a MMS, under the Messaging menu, tab New multimedia msg.

For celcom user, dial 1111 for 3G. If you use Nokia, get the 3G setup at: <https://nokiags.wdsglobal.com/standard?siteLanguageId=118>

Additional Info: MAXIS 3G

OTA at <http://www.maxis.com.my/3G/about3G.asp> and choose option 3G Phone Configuration

Manual WAP Settings

- On Desk, tab Control Panel -> Internet setup. (or similar)
- Tab New access pt. and tab No, then tab Next and key in the following:
Connection name: Maxis GPRS / **Maxis 3G**
Data bearer: GPRS
- Tab Next
Network type: IPv4
Auto-retrieve access point: (Unchecked)
Access point: net / **unet**
- Tab Next and key in the following.

Prompt password at every login: (Unchecked)

Username: maxis

Password: wap

- Tab Next then tab Finish and OK to complete the setup.
- Homepage: <http://wap.maxis.com.my/wml/index.wml>
- Session Mode: Permanent
- IP adress: 202.075.133.049
- Login Type: Automatic,
- Authentication Type: Normal

MMS Settings

OTA at <http://www.maxis.com.my/3G/about3G.asp> and choose option 3G Phone Configuration

• On Desk, tab Messaging and then press the Menu key -> Tools -> Message settings -> Multimedia message...(or similar)

• Tab Internet setup, then tab Next and key in the following:

Internet settings name: Maxis MMS

Data bearer: GPRS

• Tab Next

Network type: IPv4

Auto-retrieve access point: (Unchecked)

Access point: net / **unet**

• Tab Next and key in the following.

Prompt password at every login: (Unchecked)

Username: maxis

Password: wap

• Tab Next then tab Advanced, under Proxies, key in the following:

Protocol: HTTP

Use proxy: (Checked)

Proxy server address: 202.75.133.49

Port number: 80

• Tab OK then Finish

• Under Homepage, key in <http://172.16.74.100:10021/mmsc> and tab OK to complete the setup.

• To send a MMS, under the Messaging menu, tab New multimedia msg.

Please note that the blue color addition is for 3G Settings